

# Motor Protection Circuit Breaker

This motor protection circuit breaker is designed to protect motors from damage due to overloads and short circuits. It provides reliable protection, ensuring the longevity and efficient operation of electric motors.

Specifications					
Current setting range(A)	Power of controlled motor(KW)	Current rated (A)	Current setting range (A)	Power of controlled motor(KW)	Current rated(A)
0.1-0.16		0.16	1-1.6	0.37/0.55	1.6
0.16-0.24	0.06	0.24	1.6-2.4	0.75	2.4
0.24-0.4	0.09/0.12	0.4	2.4-4	1.1/1.5	4
0.4-0.6	0.12/0.18	0.6	4-6	2.2	6
0.6-1	0.25	1	6-10	3/4	10
1-1.6	0.37/0.55	1.6	10-16	5.5/7.5	16
1.6-2.4	0.75	2.4	16-25	11	25
2.4-4	1.1/1.5	4	22-32	15	32
3.2-5	1.5/2.2	5	28-40	18.5	40
4-6	2.2	6	36-52	22	52
5-8	3	8	45-63	-	63
6-10	3/4	10			
8-13	4/4.5	13			
10-16	7.5	16			
14-20	7.5	20			
18-25	11	25			