

# 1280Wh Portable Power Station with 1000W AC Output

This portable power station features a 1280Wh capacity and provides 1000W AC output. It is designed with multiple output ports, including AC, USB, and DC, to power a variety of devices.



## ADDITIONAL IMAGES



## Overview

### High-Capacity Portable Power Solution

This 1280Wh portable power station is engineered for high capacity, safety, and portability, making it an ideal choice for both home backup during emergencies and outdoor adventures. Utilizing a stable LiFePO4 battery chemistry, it supports 2000+ recharge cycles while maintaining over 80% capacity. With a 1000W AC output and a versatile array of charging ports, it reliably powers essential electronics, from home appliances to camping gear.

## Key Features

### Key Benefits

LiFePO4 Safety • 1280Wh Capacity • 1000W AC Output • Pure Sine Wave • Portable Design

## Technical Specifications

### Battery Performance

**1280 Wh**

Capacity

**2000 cycles**

Cycle Life

**13 kg**

Weight

### Power Output

**1000 W**

Rated Power

**2000 W**

Peak Power

## Connectivity



wechat ID



what's up ID

Versatile interface featuring multiple AC, DC, and USB output options for various devices.

## Output Ports

Port Type	Specification
AC Output	2x 1000W Pure Sine Wave
USB-C	2x 100W
USB-A	2x 18W (QC3.0)
DC Output	2x 5521 (12V/10A), 1x Cigarette Lighter (12V/10A)
Wireless	1x 10W

## Charging

### Input Methods

- AC Wall Charger (1000W)
- Solar Panel (Max 400W)
- Car Port (120W)

### Recharge Times

Method	Time
Wall Charger	1.2 Hours
Solar Panel	3.2 Hours
Car Port	11 Hours