

# Electronic Ballast 220V

This electronic ballast is designed for optimal performance and reliability. It has an input voltage of 220V, 50/60Hz and a power factor of 0.95.



## Product Overview

### High-Performance Electronic Ballast

This electronic ballast is engineered for optimal performance and reliable operation in lighting applications. Designed for a 220V input, it ensures consistent power delivery with a high power factor of 0.95. It is built to withstand diverse environmental conditions, making it a robust choice for professional lighting systems.

## Technical Specifications

Input Voltage	220V
Frequency	50/60Hz
Power Factor	0.95
Compatible Lamp Wattage	18 W

## Operating Conditions

Ambient Temperature (Ta)	-15°C to 50°C
Max Case Temperature (Tc)	70 °C

## Identification

Model Number	JY183F
--------------	--------

## Key Metrics

### Performance Summary

<b>0.95</b> Power Factor	<b>18 W</b> Lamp Power
-----------------------------	---------------------------