

# Three-Phase Electronic Energy Meter

This electronic meter measures three-phase electrical energy consumption. It supports 3x100V voltage and a 3x1.5(6)A current range.



## Product Overview

### Precision Energy Monitoring

This three-phase electronic energy meter is engineered for accurate monitoring of electrical energy consumption in industrial and commercial environments. Designed for reliability and precision, it ensures consistent performance under standard operating conditions. Its robust construction and adherence to established technical standards make it a dependable choice for energy management systems.

## Technical Specifications

|                      |                        |
|----------------------|------------------------|
| Voltage Rating       | 100 V                  |
| Current Range        | 3x1.5(6)A              |
| Standards Compliance | GB/T17215-2002         |
| Meter Type           | Electronic Three-Phase |

## Key Metrics

### Operating Metrics

**100 V**

Voltage

**6 A**

Max Current