

# Three-Phase Electronic Energy Meter

This three-phase electronic energy meter is designed for measuring electrical energy consumption. It operates on a 3x220/380V, 50Hz power supply and has an impulse constant of 3200imp/kWh.



## Overview

### Three-Phase Electronic Energy Meter

The DTS188 type H1 is a professional-grade three-phase four-wire electronic energy meter designed for accurate electrical energy consumption measurement. Engineered for reliability, it operates on a standard 3x220/380V, 50Hz power supply. This device includes advanced features such as pulse, communication, and alarm indicators, along with an integrated infrared communication port for efficient data management.

## Technical Specifications

Voltage Rating	3x220/380V
Frequency	50 Hz
Current Rating	3x1.5(6)A
Impulse Constant	3200 imp/kWh

## Compliance and Standards

Standards Compliance	GB/T 17215-2002
----------------------	-----------------

## Features

### Integrated Features

- Pulse indicator
- Communication indicator
- Alarm indicator
- Infrared communication port

## Performance Metrics

### Key Performance Metrics

**3200 imp/kWh**

Impulse Constant

**50 Hz**

Frequency