

1000W Portable Gasoline Generator

This gasoline generator has a rated output of 1000 watts at 220V and 50Hz. It can provide a peak output of 1200 watts for 10 seconds to start larger equipment.



Overview

Reliable Portable Power

This 1000W portable gasoline generator is engineered for dependable power output in various applications. Featuring an advanced engine design, it offers improved fuel efficiency and easier maintenance for professional users. Its compact and lightweight construction ensures easy portability, while robust build quality guarantees a longer service life and reduced noise levels during operation.

Engine & Performance

Engine Model	GX100
Displacement	98 cc
Noise Level	68 dB(A)

Power Output

Key Power Metrics

1200 W Max AC Output	1000 W Rated AC Output	100 W DC Output
--------------------------------	----------------------------------	---------------------------

Voltage Specifications

- AC Output: 220V (5.4A max / 4.5A rated)
- DC Output: 12V (8.3A)
- Frequency: 50Hz

Fuel & Operation

Run Time

Load Condition	Duration
Rated Load	8.5 hrs
1/2 Load	13 hrs

Fuel Tank Capacity	5 L
--------------------	-----

Physical Attributes

Weight

26 kg

Dry Weight

28 kg

Gross Weight

Dimensions (L x W x H)

485 x 415 x 430 mm

Logistics

Container Loading (20'/40')

330 / 792 units

Features

Key Features

Portable • Low Noise • Fuel Efficient • Recoil Start • AVR Equipped