

12-Channel Powered Mixer with USB, SD Card, and Recording

This 12-channel powered mixer is equipped with USB and SD card slots for versatile audio playback and recording. A built-in display allows for easy navigation and control.



Overview

Professional 12-Channel Mixing Solution

The PS-1200MG is a versatile 12-channel powered mixer designed for live performances, karaoke, and recording applications. It features high-performance mic preamps with phantom power, integrated DSP effects, and multi-channel EQ control. With built-in USB/SD recording capabilities and a robust amplifier, it provides a comprehensive all-in-one audio management system for venues and studios.

Performance Metrics

Audio Specifications

0.05 %

Total Harmonic Distortion (THD)

64 dB

S/N Ratio

4 V

Max Output

Connectivity & Inputs

Input Sensitivity Levels

Input Type	Sensitivity
Mic	-60dB
Line	-34dB
SUB In	+4dB
Tape In	-10dB

Channel Setup

7 Mono Channels, 1 Stereo Channel, USB Input, SD Card Input, 48V Phantom Power

Power & Output

Amplifier Output Power

- 2 x 400W (4 Ω)
- 2 x 800W (4 Ω)

Features

Ideal Applications

Karaoke • Stage Performance • KTV • Home Entertainment • Professional Meetings

Key Functions

- Built-in 16 DSP Effects
- Direct recording to USB flash drive
- 4-group high precision level display
- 3-band EQ per channel