

16mm Mushroom Reset Emergency Push Button Switch

This 16mm mushroom reset button is an emergency stop push button switch. It features a 16mm mounting diameter and is available in multiple colors.



Product Overview



Specializing in production of buttons and indicators since 1997

Red mushroom actuator for emergency stop applications.

Industrial Emergency Reset Button

The XDL16-11M is a high-performance 16mm mushroom-head push button switch engineered for critical control circuits and emergency stop applications. Constructed with zinc alloy and high-grade anti-flam materials, it features silver alloy contacts to minimize electrical erosion and ensure long-term reliability. This versatile series is compliant with international standards, making it an ideal choice for distribution cabinets, machinery control panels, and communication networks.

Technical Specifications



XDL16-11M

Mushroom button

1NO+1NC
2NO+2NC



● Red
● Green
● Yellow
○ White
● Blue

XDL16-11M
 XDL16-11ML
 XDL16-22M
 XDL16-22ML



Dimensional diagram showing 16mm mounting diameter and configuration options.

Featured Metrics

660 V

Rated Insulation Voltage

10 A

Conventional Heating Current

2.5 kV

Withstand Voltage

60 cd/m²

Lamp Brightness

Environment

- Operating temperature: -25°C to +50°C
- Relative humidity: < 85%
- Altitude: < 2,000m
- Protection grade: IP40/IP55
- Pollution grade: 3

Performance Lifecycle

Parameter	Pushbutton	Selector Switch
Mechanical Life	1,000,000 cycles	500,000 cycles
Electrical Life	5,000,000 cycles	250,000 cycles

Certifications & Standards

Certifications

CE, ISO 9001, ROHS, UL, GB/T14048.1, IEC60947-5-1