

2000W Digital Inverter Generator

This 2000W inverter generator provides a stable AC output of 230V at 50Hz, along with a 12V DC output and a USB port. It features overload protection and low oil alarm.



ADDITIONAL IMAGES



Overview

High-Efficiency Digital Inverter Generator

The GI2000CF is a compact, digital inverter gasoline generator designed for reliable power delivery. Featuring a 4-stroke OHV engine, it provides a stable 1.6kW rated power output, making it ideal for sensitive electronic equipment. With a durable, forced air-cooled design and intuitive control panel, this generator ensures consistent performance for professional and outdoor applications.

Power Output

Key Power Metrics

1.6 kW

Rated Power

2 kW

Max Power

230 V

Rated Voltage

Electrical Specifications

- AC Output: 230V / 50Hz
- DC Output: 12V / 5A
- Power Factor: 1.0
- USB Output: 2.1A

Engine & Performance

Engine Specifications

Feature	Specification
Engine Type	Forced Air-cooled, 4-stroke, OHV
Displacement	105.6cc
Fuel Type	Gasoline
Starting System	Recoil Start

Operational Performance

- Fuel Tank Capacity: 3.2 L
- Run Time: 3.2 hours (at rated power)
- Sound Power Level: 71 dB(A)

Compliance & Safety

Compliance Standards

ISO 8528 • ISO 6826

Safety Features

Overload Protection, Low Oil Alarm, Overload Alarm, Output Indicator

Logistics

Shipping & Packaging

Metric	Value
Gross Weight	23 kg
Net Weight	21.3 kg
Carton Dimensions	550 x 315 x 460 mm
Container Qty (20'/40'/40'HQ)	368 / 760 / 760