

# Digital Audio Mixer for Live Broadcasting

This digital audio mixer is designed for online live broadcasting. It features multiple input channels, phantom power, Bluetooth connectivity, and a 24-bit/192kHz processor for high-quality audio processing.



## ADDITIONAL IMAGES



## Overview

### Professional Digital Audio Mixer

This versatile 6/8 channel mixer is designed specifically for high-quality live broadcasting and audio production. It features robust microphone and line inputs, integrated Bluetooth connectivity, and a powerful 24-bit/192kHz DSP processor with 16 built-in effects. Ideal for streamers and podcasters, it provides precise control over vocals and instruments with dedicated EQ and monitoring capabilities.

## Connectivity & Inputs

### Input Channels

- 2x Mono (MIC/LINE)
- 2x Stereo (LINE)

### Output Channels

- 2x Stereo
- 1x PHONES

### Bluetooth Connectivity

Yes

## Audio Processing

### DSP Effects

16 types

### Phantom Power

+48V

### Channel Processing Features

PAD 26dB, HPF 80Hz, EQ High/Low Control

## Power & Performance

### Power Supply

**100 V**

AC Voltage Min

**240 V**

AC Voltage Max

**12 V**

DC Output

### Power Consumption

Model	Consumption
6 Channel	7.3W
8 Channel	9.2W