

Digital Electronic Lock Home Safe

This digital safe features an electronic lock that can be programmed with a 3-8 digit code and includes an emergency override key. It is constructed with durable materials and includes pre-drilled mounting holes for easy installation.



ADDITIONAL IMAGES



Product Overview

Compact Security for Valuables

This digital electronic safe is an ideal storage solution for home or office environments. It features a user-programmable 3-8 digit electronic lock, reinforced by a dual-bolt solenoid system for reliable access control. The compact design includes pre-drilled mounting holes and a protective carpeted interior, ensuring your jewelry, cash, and important documents remain secure and scratch-free.

Technical Specifications

Weight and Capacity

5.5 kg

Weight

8.5 L

Capacity

External Dimensions

200mm (H) x 310mm (W) x 200mm (D)

Internal Dimensions

197mm (H) x 307mm (W) x 140mm (D)

Construction

Material Thickness

| Component | Thickness |
|-----------|-----------|
| Door | 4mm |
| Body | 1.5mm |

Security Features

Feature

| | |
|------------------------|---|
| Code: | Open & close 3 or 8 digit code |
| Display: | 3 indicator lights(green,red,and yellow),indicate open,low battery and warning. |
| Working System: | Use the knob to open and close with a solenoid system |
| Bolt: | One-way locking bolts(2 bolts with Dia.20mm) |
| Override Key: | Supply the override key for emergency use |
| Interior: | Include the protective floor mat |
| Battery: | Run on 4 x 1.5V AA batteries |
| Fixing: | Pre-drilled holes at the bottom and back(fixings include |

Key features include a programmable electronic keypad, solenoid locking mechanism, and dual bolt security.

Locking System

- Electronic digital keypad (3-8 digit code)
- Solenoid system with manual knob
- Emergency override key provided
- Dual locking bolts (13.5mm-20mm diameter)

Status Indicators

Open status, Low battery alert, Warning alert

Power & Installation



Code
Open & Close with 3-8 digit code.



Indicator
3 indicator lights (green, red and yellow), indicate open,low battery and warning.



Working system
Use the Knob to open and close with a solenoid system.



Bolt
One-way locking bolts. (2 bolts with Φ 20mm)



Reset button
Change the code easily with reset button.



Override key
Supply the override key for emergency use.



Interior
Include the protective floor carpet.



Battery
Run on 4x1.5 V AA batteries.



Fixing
Pre-drilled holes at the bottom and back (fixings included).

The interior is equipped with a protective carpet, and the unit includes pre-drilled holes for secure anchoring.

Power Source

4 x 1.5V AA batteries

Installation Options

Pre-drilled bottom holes, Pre-drilled back holes