

# Fluorescent Lamp Electronic Ballast

Electronic ballast designed for operating fluorescent lamps. It provides efficient and reliable starting and operation of fluorescent lighting systems and is suitable for industrial and commercial lighting applications.



## Product Overview

### High-Efficiency Electronic Ballast

This electronic ballast is engineered for the reliable operation of fluorescent lighting systems in industrial and commercial environments. It ensures efficient starting and consistent performance across various lamp wattages. Designed for durability and stability, this unit maintains a high power factor, making it an ideal choice for professional lighting infrastructure.

## Electrical Specifications

Input Voltage	220V-240V
Rated Frequency	50 Hz
Rated Current	0.17 A
Power Factor (cos) $\phi$	$\geq 0.95$

## Operational Limits

Ambient Temperature (Ta)	50 °C
Max Case Temperature (Tc)	75 °C

## Compatibility

### Compatible Lamp Types

- 2x18W
- 36W

## Identification

Model Number	JF0802
--------------	--------