

Gasoline Generator Set

This gasoline generator set is designed for reliable power generation. It features a robust construction with a protective frame, ensuring durability and portability.



Overview

Reliable Power Generation

This gasoline generator set is engineered for consistent and dependable power output, making it an ideal solution for various portable power needs. Featuring a 4-stroke, air-cooled engine and a brushless alternator, the unit is designed for durability and ease of maintenance. With a 15-liter fuel tank, it offers extended operation hours, ensuring you have power when you need it most.

Engine Performance

Engine Specifications

163 cc

Displacement

5.5 HP

Rated Power

3600 rpm

Rated Speed

Engine Model

OY168

Starting System

Recoil, Electric Start

Generator Output

Power Output

2 kW

Rated Output

2.3 kW

Max Output

Supported Voltages

- 110
- 120
- 220
- 230
- 240

Operational Details

Fuel Tank Capacity

15 L

Continuous Operation

13 H

Operating Noise Level

67 dB

Physical Dimensions

Size and Weight

Attribute	Value
Dimensions (LxWxH)	610x445x445 mm
Dry Weight	38 kg