

Portable Inverter Generator 2100W

This portable inverter generator delivers 1700 running watts and 2100 starting watts. It includes a variety of outlets and safety features such as overload protection and low oil shutdown.



ADDITIONAL IMAGES



Overview

Clean and Versatile Power

The 2100W Portable Inverter Generator provides reliable and quiet electricity, perfect for sensitive electronics, camping equipment, and small appliances. Designed with an efficient 79.7cc engine and advanced inverter technology, it delivers stable power output with minimal noise. Its lightweight and compact construction ensures excellent portability for professional and recreational use.

Performance Metrics

Key Performance Indicators

2100 W

Starting Output

1600 W

Rated Output

61 dB(A)

Noise Level @ 7m

Technical Specifications

Engine Specifications

Feature	Specification
Displacement	79.7cc
Engine Type	4-Stroke, OHV, Air Cooled
Cylinders	Single
Starting Method	Recoil
Fuel System	3.8 L

Operational Features

Available Outlets

- 120 VAC 20A Outlet
- 12 VDC 5A Outlet
- 5 VDC 2.1A USB Port

Mode Settings

ECO Mode • Parallel Capability

Safety and Protection

Overload Protection, DC Breaker, Floating Neutral, Low Oil Shutdown