

Wall Mount Multi-Channel Zoner Amplifier with Bluetooth USB FM Radio

This wall-mount multi-channel zoner amplifier features Bluetooth connectivity for wireless audio streaming, a USB port for media playback, and an FM radio tuner. It is designed for multi-zone audio systems, offering independent volume control for each channel.



ADDITIONAL IMAGES



Product Overview

Professional Multi-Channel Audio Distribution

This wall-mountable multi-channel zoner amplifier is designed for versatile audio distribution in commercial and residential settings. It features four independent channels of AB-class amplification, providing 80W RMS output at 4 ohms per channel. With integrated Bluetooth, USB playback, and FM radio, it offers flexible input options for diverse audio requirements.

Performance Specifications

Amplifier Power

80 W

RMS Power per Channel

4 CH

Channels

Amplifier Class

AB-class

Impedance

4 Ω

Connectivity & Inputs

Input Sensitivity/Impedance

Input Type	Sensitivity	Impedance
MIC	-35dB	2K Ω
LINE	-3dB	20K Ω

Supported Inputs

Bluetooth, USB, FM Radio, MIC, LINE

Controls & Features

Control Options

- Level control per channel
- Individual Low & High EQ per output
- Integrated USB/FM/Bluetooth player

Technical Details

Power Requirements	AC115V or AC230V
Power Consumption	180 W

Physical Specifications

Dimensions (WxDxH)	384 x 95 x 474 mm
Net Weight	8 kg

Logistics

Container Capacity (20'/40'/40'HC)	620 / 1260 / 1500 units
------------------------------------	-------------------------